

# ST5

## Streamer



The ARCAM ST5 is the high resolution upgrade for our Radia integrated amplifiers. The slim form factor includes a control link to these amplifiers, allowing the 2 components to act as one from your device. Sonically, this combination offers better sound quality due to the benefits of isolated components with individual power supplies.

The ARCAM ST5 provides an inclusive feature set supporting the majority of smart phones and tables, as well as popular streaming services. Connect the ST5 to your home network with Wi-Fi or Ethernet to enjoy instant playback using Apple Airplay or Google Cast.

The ST5 will playback music directly from Spotify Connect, Tidal Connect, Qobuz Connect, and it is Roon Ready, all with Hi-res and MQA support. All digital audio is output on the analogue outputs using an ESS ES9018 high resolution DAC with time domain jitter elimination for perfect sound, every time.

### Features

- Perfect match for the ARCAM A5+ and A15+ - with comms link for input and volume control
- Spotify Connect
- Tidal Connect
- Qobuz Connect
- Apple Airplay
- Google Cast
- Roon Ready
- Works with new ARCAM Radia app - for Wi-Fi setup and internet radio presets and Podcasts
- Hi-Res Audio - up to 24 bit / 192 kHz
- Plastic Free Packaging



<b>Services</b>	
Works with (apps)	ARCAM Radia Spotify Connect Tidal Connect Qobuz Connect Room
Works with (services)	Apple Airplay Google Cast
ARCAM Radia supported services (Global)	Internet Radio Podcasts Amazon Music Unlimited UPnP USB Media (using USB-A mass storage input)
<b>Audio Section</b>	
Supported Hi-res media:	FLAC, WAV (LPCM), MQA, AAC, ALAC, AIFF, DSD (up to 128)
Supported Hi-res Bit depth:	16, 24
Supported samples rates (kHz):	44.1, 48, 88.2, 96, 176.4, 192
Supported media:	MP3, MP4, OGG, WMA
Supported Bit depth:	16
Supported samples rates (kHz):	44.1, 48
Gapless Playback:	Yes
Outputs:	1x Analogue Stereo (RCA) pair 1x Digital S/PDIF Coaxial (RCA) 1x Digital S/PDIF Optical (Toslink)
Frequency response (filter 1):	20Hz—20kHz ± 0.05dB
<b>General</b>	
Mains voltage	100V–120V or 220–240V, 50-60Hz
Power consumption	12W
Power consumption (Eco standby)	<0.5W
Dimensions W x D (including speaker terminals) x H (including feet)	431 x 344 x 58mm
Weight (net)	3.58 kg
Weight (packed)	6.6 kg
Supplied accessories	Mains lead(s) Remote control with 2 x AAA batteries Control Cable Quick Start Guide Important Safety Instructions